



## Display

- 3½ digits LCD with maximum reading of 2000.
- Overload indication: "OL".
- Low battery indication: "BATT".

## FUNCTIONS

- Function keys: ON/OFF, DC/AC MAX.
- Test ranges: ACV, ACA, DCV, DCA,  $\Omega$ , Diode, Transistor, Continuity, Frequency,
- AC/DC 10A, Inductance(H), Capacitance.

## DIMENSION

- Size: 186x86x39mm(LxWxH).
- Weight: About 390g (including battery).

Model	YF-220A
Display counts	4000
AC A	10 $\mu$ A~400mA
DC A	10 $\mu$ A~400mA
AC Voltage	0.1mV~500V
DC Voltage	0.1mV~500V
Resistance	0.1 $\Omega$ ~40M $\Omega$
Continuity buzzer	YES(<40 $\Omega$ )
Diode	1mV~4.000V
Frequency	-----
Autorange	-----
Auto power OFF	YES
Data hold	YES
MAX /MIN	-----
REL(ZERO)	YES
Transistor hFE TEST	-----
Capacitance	0.01n~100 $\mu$ F